

TESTAVIT SCHUKI 3 LCD

Socket outlet testers

Using the new Testavit Schuki 1 LCD and 3 LCD, specialists easily check to see if sockets, cable drums or connecting cables are correctly connected in 230 V installations. Due to three LEDs, the connection status can be quickly and clearly determined. In addition, through the finger contact, it can be tested to see whether an impermissible, high contact voltage is applied at the protective earth connection. In addition, using the Testavit Schuki 1 LCD, a 30 mA FI circuit breaker (RCD) can be triggered via a pushbutton.

How you benefit:

- | Quick and safe checking of installations
- | Finger contact to check the protective earth connection
- | FI test (Schuki 1 LCD)
- | FI test (30 mA @ 230 V AC)

Specifications

| Technical Data | TESTAVIT SCHUKI 3 LCD |
|-----------------------|-------------------------------|
| Display | Optical, LCD and LED |
| Operating Voltage | 230 V, 50 Hz |
| RCD Triggering | No |
| Error Current | no |
| Protection | IP 40 |
| Overload Category | CAT II 300 V |
| Standard | IEC/EN 61010-1 (DIN VDE 0411) |
| Operating temperature | 0–50 °C |
| Dimension | 60 × 60 mm |
| Weight | 54 g |
| Scope of Delivery | incl. operating instructions |

